••• verifone

https://verifone.cloud/docs/in-person-payments/global-payment-application-gpa/gpa-intercard-userguide/management Updated: 27-Oct-2023

Management Functions

This section covers the management functions of the terminal.

Screen Information	Rebranded Screen Information					
	3% @14:42					
ବ 🔻 🗘 100% ୮୭ 13	3:47 Management					
Management	Wanagement					
1 About	About					
2 Settings	Settings					
3 Diagnostics	Diagnostics					
	Back					
Back						

About

The application version, build number, a profile is displayed. The terminal operating system version and terminal model versions may also be displayed.

Step Instruction

Screen Information

	1	<i>₽</i>			7 10	00% @ 13:4 7	<->				3%@14:42	
	Terminal displays information		V	erifo	ne [.]		GPA Inform	nation				
		æ	GPA Information			gpa-ic		1.6.0.0-R1-120				
		GPA Solution			GPA				3.4.0.0-			
		GPA				2.2.0.2-18	SDI Client			3.4	4 0-RC1-15	
1		GPA Core				2.2.0.2-18	Host: INTE	RCARD			2.5.0	
		SDI Client				1.3.0.2.15	ic vhq			1.6.	0.0-RC1-117	
		Intercard Host				2.0.0	2.0.0 ic uiptrb			1.6.0.0-RC1-102		
		ic vha	11050		1.1.0	.1-BC1-12	ic config	,		1.6.	0.0-RC1-117	
		ic ui			1.1.0	.1-RC1-12	en rebrand	1		3	4.0-RC1-18	
		ic slver			1.1.0	.1-RC1-12	NEXO				.4.0-101-13	
		ic config			1.1.0	.1-RC1-12			_			
		ie comg	-	-	-							
	about the	∰	4	Y	П		GPA	ADK	Comm	Device	Battery	
	application	GPA	ADK	Comr	Device	Batte			\sim	â		
	application.	щ	~			4			$\langle \vee \rangle$	8		
		- O		\checkmark	От		Memory	Sponsor	ADE	Keys	Mobile	
		Mem	Spon:	ADE	Keys	Mobile						
					•	•		<u> </u>	Ж			
		•	<>	*	•	•	WIFI	ETH	Bluetoo	EMV	Mercha	
		WIEI	стц	Diret.	EM17	March						
				_								
									Print			

Settings

Communications

The Communication Control Panel (CCP) allows the user to access the following functions:

- Set /change the network configuration parameters
- Run simple network diagnostics
- Report the network status

The most important information is on the main screen:

- The type of communication (Ethernet, GPRS, Wi-Fi, Bluetooth)
- The current connection status (connected/not connected)
- The base CCP menu (Status, Configuration, Diagnostic)

For more information, refer to Setting Connection

Set Language

The Set Language screen allows the user to select the required language.

Step Instruction		Screen Information	Rebranded Screen Information		
	ଚ	V 100% @13:47	\Leftrightarrow	3%@14:42	
		Set Language	Set Language		
The User is prompted		Please Select	Please Select		
to select the menu option,	1	English	Português		
scroll until 1 Set Language	2	Español	English	\mathbf{v}^{*}_{i}	
operation appears, or enter the	3	Français	Español		
number for the operation.	4	Português	Français		

CP Manual Launch

Use this option to launch a Commerce Plugin. If Commerce Plugins are configured, a list of applications will be displayed.

Training Mode

Training Mode is a facility that enables the user to interact with the application for demo and training purposes.

Once the application enters 'Training Mode', the User should be able to access all menus and perform all transaction types as if the terminal was in normal processing mode.

Step Instruction

Screen Information





Call TMS (Terminal Management System)

Selecting this option downloads any available updates from the TMS. The terminal will display "No Updates Available" if there is nothing to download.

Step Instruction

Screen Information









Change Password

The terminal is programmed with an Admin password which is required for refunds, void transactions, and some protected terminal functions. This password is a security measure to ensure only authorized personnel can access this functionality on the terminal.

The system supports 3 password roles:

- Admin typically the User, store owner, or the store supervisor
- Manager
- Cashier

Step Instruction

Screen Information











Diagnostics

EMV Debug Report

The EMV Debug Report is a feature, which allows the user to print EMV data which may be asked for by the Verifone Helpdesk if the User calls requesting assistance.

Step Instruction

Screen Information



