

GET_PARM

This command allows the POS to retrieve SCA parameter values from the payment device (TranslateConfig.xml).

Device UI Required: No

Request Packet

Field	Rule	Type	Minimum	Maximum	Value(s)	Description
FUNCTION_TYPE	Required	Static value	N/A	N/A	DEVICE	Type of function
COMMAND	Required	Static value	N/A	N/A	GET_PARM	Command name
PARAM	Required	Character	1			Pipe-delimited list of parameters to retrieve specified by POS. Only listed parameters will appear in the response. Refer Vantiv Direct or Engage Parameters guide, Config.sys or config usr1 name column for parameter names. Example: IPPAH IPPAP , MID
POS_RECON	Optional	Character	1	30		POS reconciliation. POS Reconciliation field to be echoed back in response to POS. Example: RetailPOS1

Field	Rule	Type	Minimum	Maximum	Value(s)	Description
COUNTER	Required	Numeric	1	10		COUNTER is used for a given MAC label. Each COUNTER should be higher than the last one. This is used to authenticate the POS. Example: 100
MAC	Required	Base64 Encoded Data	N/A	N/A	N/A	Message Authentication Code. This is used to authenticate the POS.
MAC_LABEL	Required	Character	1	50		Associated label that tells the device which MAC_KEY to use to decrypt the value of MAC. This is used to authenticate the POS. Example: REG1

Example

Following is an example of request packet

```

<TRANSACTION>
<FUNCTION_TYPE>DEVICE</FUNCTION_TYPE>
<COMMAND>GET_PARM</COMMAND>
<PARAM>IPPAH|IPPA</PARAM>
<COUNTER>1</COUNTER>
<MAC> ... </MAC>
<MAC_LABEL>REG2</MAC_LABEL>
</TRANSACTION>

```

Response Packet

Field	Type	Value	Description
RESPONSE_TEXT	Character		Processor response text. Example: Operation SUCCESSFUL
RESULT	Character		This indicates the Result details. Example: OK
RESULT_CODE	Numeric	Expected result code: -1, 59001, 59006, 59040	This indicates the result code. Refer to Result/Error Codes for details.
TERMINATION_STATUS	Character	SUCCESS or FAILURE	This indicates the transaction termination status. This is the overall status of the transaction irrespective of approved or declined. Like, if the output is generated then the status is SUCCESS and if no output is generated then the status will be FAILURE.
PARAM	Character		Returns the list of parameters. Example: IPPAH=certssl.protectedtransactions.com IPPAP=443
POS_RECON	Numeric		POS reconciliation field echoed back if sent in request. Example: RetailPOS1
COUNTER	Numeric		Echoes counter sent in the request. Example: 100

Example

Following is an example of response packet

```
<RESPONSE>
<RESPONSE_TEXT>Operation SUCCESSFUL</RESPONSE_TEXT>
<RESULT>OK</RESULT>
<RESULT_CODE>-1</RESULT_CODE>
<TERMINATION_STATUS>SUCCESS</TERMINATION_STATUS>
<COUNTER>100</COUNTER>
<PARAM>IPPAH=certssl.protectedtransactions.com|IPPAP=443</PARAM>
</RESPONSE>
```