

OptFlags Parameters

This table describes the required parameters used for optional flags configurations.

Config.usr1/Parameter DLD Name	Description	Valid/Max Values	Default Value	Name in PropertiesData.xml
AMEXCTLS	This parameter set the Amex CTLS TTQ value or mode.	<ul style="list-style-type: none"> • 1 - CTLS MSD Mode • 2 - CTLS MSD/EMV Mode 	2	AMEXCTLS
CONTACTLESSEENABLED	This parameter is used to enable or disable contactless processing.	<ul style="list-style-type: none"> • 0 - Disable • 1 - Enable 	1	CTLSEnable
DPASTTQ	This parameter sets the DPAs TTQ value or Mode for accepting EMV CTLS cards (TTQ = Terminal Transaction Qualifier).	<ul style="list-style-type: none"> • 1 - MSD • 2 - MSD/EMV • 3 - EMV 	<ul style="list-style-type: none"> • 1 • 3 for UGP 	DPASTTQ
FastPayment	Quick payment service eliminates the need for signatures in a fast paced environment. Customer will not be asked to provide a signature for transactions above the configured CVM limit. The service is designed to speed up the time customers are waiting in line.	<ul style="list-style-type: none"> • 0 - Disable • 1 - Enable 	0	FastPayment
MCMChip	Reserved for future use. This parameter sets the McMCHIP TTQ value or Mode for accepting EMV CTLS cards	<ul style="list-style-type: none"> • 1 - MSD • 2 - MSD/EMV 	1	MCMChip
MobileSupport	Future use. This parameter is used to enable or disable mobile support.	<ul style="list-style-type: none"> • 0 - Disable • 1 - Enable 	1	MobileSupport
OPTINVISADEBIT	This parameter is used to enable or disable Visa Debit opt out option for cards with country code of CAN.	<ul style="list-style-type: none"> • 0 - Disable • 1 - Enable 	1	VisaDebit

Config.usr1/Parameter DLD Name	Description	Valid/Max Values	Default Value	Name in PropertiesData.xml
PDOLSupport	This parameter is used to enable or disable support of Processing Options Data object List - tags in this object list are provided by the terminal to be processed as part of the GPO. This data is necessary to begin processing EMV data.	<ul style="list-style-type: none"> • 0 - Disable • 1 - Enable 	0	PDOLSupport
SoftCardSupport	This parameter is used to enable or disable Soft Card NFC support.	<ul style="list-style-type: none"> • 0 - Disable • 1 - Enable 	0	SoftCardSupport
ValueLinkSupport	This parameter is used to enable or disable ValueLink gift card support.	<ul style="list-style-type: none"> • 0 - Disable • 1 - Enable 	0	ValueLinkSupport
VISATTQ	This parameter sets the Visa TTQ value or Mode for accepting EMV CTLS cards.	<ul style="list-style-type: none"> • 1 - MSD • 2 - MSD/qVSDC • 3 - qVSDC • 9 - Not supported 	3	VisaTTQ