

Defines for LED IDsLED control

LED numbers in [EMV_CTLS_LED\(\)](#)
[More...](#)

Collaboration diagram for Defines for LED IDs:



Macros

```
#define CONTACTLESS\_LED\_FIRST 0x01
    first contactless LED More...
#define CONTACTLESS\_LED\_SECOND 0x02
    second contactless LED More...
#define CONTACTLESS\_LED\_THIRD 0x04
    third contactless LED More...
#define CONTACTLESS\_LED\_FOURTH 0x08
    fourth contactless LED More...
#define CONTACTLESS\_LED\_BLUE CONTACTLESS\_LED\_FIRST
    first LED for signalling field on More...
#define CONTACTLESS\_LED\_YELLOW CONTACTLESS\_LED\_SECOND
    second LED indicating chip card communication More...
#define CONTACTLESS\_LED\_GREEN CONTACTLESS\_LED\_THIRD
    third LED "Card read successfully" More...
#define CONTACTLESS\_LED\_RED CONTACTLESS\_LED\_FOURTH
    fourth LED indicating error More...
#define CONTACTLESS\_LED\_0 CONTACTLESS\_LED\_FIRST
    Contactless LED 1,. More...
#define CONTACTLESS\_LED\_1 CONTACTLESS\_LED\_SECOND
    Contactless LED 2,. More...
#define CONTACTLESS\_LED\_2 CONTACTLESS\_LED\_THIRD
    Contactless LED 3,. More...
```

#define [CONTACTLESS_LED_3](#) [CONTACTLESS_LED_FOURTH](#)

Contactless LED 4,. [More...](#)

#define [CONTACTLESS_LED_ALL](#) 0x0F

All Contactless LEDs. [More...](#)

#define [CONTACTLESS_LED_LOGO](#) 0x80

CTLS Logo LED (only UX family and M425/M450-Plus-A), not combinable with other LEDs. [More...](#)

Detailed Description

LED numbers in [EMV_CTLS_LED\(\)](#)

Macro Definition Documentation

? [CONTACTLESS_LED_0](#)

#define CONTACTLESS_LED_0 [CONTACTLESS_LED_FIRST](#)

Contactless LED 1,.

Deprecated:

because confusing, use [CONTACTLESS_LED_FIRST](#) instead

? [CONTACTLESS_LED_1](#)

#define CONTACTLESS_LED_1 [CONTACTLESS_LED_SECOND](#)

Contactless LED 2,.

Deprecated:

because confusing, use [CONTACTLESS_LED_SECOND](#) instead

? [CONTACTLESS_LED_2](#)

#define CONTACTLESS_LED_2 [CONTACTLESS_LED_THIRD](#)

Contactless LED 3,.

Deprecated:

because confusing, use [CONTACTLESS_LED_THIRD](#) instead

? CONTACTLESS_LED_3

#define CONTACTLESS_LED_3 [CONTACTLESS_LED_FOURTH](#)

Contactless LED 4,.

Deprecated:

because confusing, use [CONTACTLESS_LED_FOURTH](#) instead

? CONTACTLESS_LED_ALL

#define CONTACTLESS_LED_ALL 0x0F

All Contactless LEDs.

? CONTACTLESS_LED_BLUE

#define CONTACTLESS_LED_BLUE [CONTACTLESS_LED_FIRST](#)

first LED for signalling field on

? CONTACTLESS_LED_FIRST

#define CONTACTLESS_LED_FIRST 0x01

first contacless LED

? CONTACTLESS_LED_FOURTH

#define CONTACTLESS_LED_FOURTH 0x08

fourth contacless LED

? CONTACTLESS_LED_GREEN

#define CONTACTLESS_LED_GREEN [CONTACTLESS_LED_THIRD](#)

third LED "Card read successfully"

? CONTACTLESS_LED_LOGO

```
#define CONTACTLESS_LED_LOGO 0x80
```

CTLS Logo LED (only UX family and M425/M450-Plus-A), not combinable with other LEDs.

? CONTACTLESS_LED_RED

```
#define CONTACTLESS_LED_RED CONTACTLESS\_LED\_FOURTH
```

fourth LED indicating error

? CONTACTLESS_LED_SECOND

```
#define CONTACTLESS_LED_SECOND 0x02
```

second contacless LED

? CONTACTLESS_LED_THIRD

```
#define CONTACTLESS_LED_THIRD 0x04
```

third contacless LED

? CONTACTLESS_LED_YELLOW

```
#define CONTACTLESS_LED_YELLOW CONTACTLESS\_LED\_SECOND
```

second LED indicating chip card communication