

## GET\_DEVICENAME

This command retrieves the device name stored on the payment device.

**Device UI Required:** No

### Request Packet

Field	Rule	Type	Minimum	Maximum	Value(s)	Description
FUNCTION_TYPE	Required	Static value	N/A	N/A	DEVICE	Type of function.
COMMAND	Required	Static value	N/A	N/A	GET_DEVICENAME	Command name
POS_RECON	Optional	Character	1	30		POS reconciliation. POS Reconciliation field to be echoed back in response to POS. <b>Example:</b> RetailPOS1
COUNTER	Required	Numeric	1	10		COUNTER is used for a given MAC label. Each COUNTER should be higher than the last one. This is used to authenticate the POS. <b>Example:</b> 100
MAC	Required	Base64 Encoded Data	N/A	N/A	N/A	Message Authentication Code. This is used to authenticate the POS.

Field	Rule	Type	Minimum	Maximum	Value(s)	Description
MAC_LABEL	Required	Character	1	50		Associated label that tells the device which MAC_KEY to use to decrypt the value of MAC. This is used to authenticate the POS. <b>Example:</b> REG1

#### Example

Following is an example of request packet

```
<TRANSACTION>
<FUNCTION_TYPE>DEVICE</FUNCTION_TYPE>
<COMMAND>GET_DEVICENAME</COMMAND>
</TRANSACTION>
```

#### Response Packet

Field	Type	Value	Description
RESPONSE_TEXT	Character		Processor response text. <b>Example:</b> Operation SUCCESSFUL
RESULT	Character		This indicates the Result details. <b>Example:</b> OK
RESULT_CODE	Numeric	Expected result code: -1, 59006, 59040	This indicates the result code. Refer to <a href="#">Result/Error Codes</a> for details.

Field	Type	Value	Description
TERMINATION_STATUS	Character	SUCCESS or FAILURE	This indicates the transaction termination status. This is the overall status of the transaction irrespective of approved or declined. Like, if the output is generated then the status is SUCCESS and if no output is generated then the status will be FAILURE.
DEVICENAME	Character		Device name stored on the payment device. May be null if no device name was set up at network configuration. <b>Example:</b> LANE1
POS_RECON	Character		POS reconciliation field echoed back if sent in request. <b>Example:</b> RetailPOS1
MAC_LABELS	List		List of MAC labels. <b>Example:</b> P_29K19J P_48HDYL P_6QCE5  P_6JP4D7 P_7528ZO P_7WO2PW  P_89G499 P_9BGLEO P_FEZ2AP  P_GLZOFA P_IJA 6Z P_LZIY1G P_ RD8FDD P_XO95BS P_Y3V1Q0 P_ _Z7I2I
COUNTER	Numeric		Echoes counter sent in the request. <b>Example:</b> 100

#### Transaction Performance Metric

##### Note

These fields are returned, if SCAPERFMETRIC parameter ([Application Parameters](#)) is enabled.

Field	Type	Value	Description
-------	------	-------	-------------

UI_TIME	Time	<p>This indicates the time duration, for which the device screen is displayed (like error message, prompt screen, remove card screen) till any user action is performed in the command execution flow. This field is not applicable to capture the time for the Processing, Authorizing and transaction status screen. The format of the returned value would be S.sss, where S is seconds (this can be 0 to any positive integer) and sss is milliseconds. In case of any insignificant time or 0.000 value, will not be returned in the response. <b>Example:</b> <code>&lt;UI_TIME&gt;44.028&lt;/UI_TIME&gt;</code></p>
HOST_TIME	Time	<p>This indicates the time taken for the Connection to the host, sending request and receives data from the host. This field also take the cumulative time for multiple requests which may sent to the host during the transaction including two legged transactions, timeout requests, Auto Last Tran requests, DCC, Credit app proxy. The format of the returned value would be S.sss, where S is seconds (this can be 0 to any positive integer) and sss is milliseconds. In case of any insignificant time or 0.000 value, will not be returned in the response. <b>Example:</b> <code>&lt;HOST_TIME&gt;1.389&lt;/HOST_TIME&gt;</code></p>

CMD_TIME	Time	<p>This field indicates the total amount of time for a command, which is executed by the application from request received to the response sent. The format of the returned value would be S.sss, where S is seconds (this can be 0 to any positive integer) and sss is milliseconds. In case of any insignificant time or 0.000 value, will not be returned in the response. <b>Example:</b> &lt;CMD_TIME&gt;70.765&lt;/CMD_TIME&gt;</p>
----------	------	---

#### Example

Following is an example of response packet

```
<RESPONSE>
<RESPONSE_TEXT>Operation SUCCESSFUL</RESPONSE_TEXT>
<RESULT>OK</RESULT>
<RESULT_CODE>-1</RESULT_CODE>
<TERMINATION_STATUS>SUCCESS</TERMINATION_STATUS>
<DEVICENAME>POINTSCA</DEVICENAME>
<MAC_LABELS>
P_29K19J|P_48HDYL|P_6QCE5|P_6JP4D7|P_7528ZO|P_7WO2PW|P_89G499|P_9BGLEO|P_FEZ2AP|P_GLZOFA|P_IJAJ6Z|P_LZIY1G|P_RD
8FDD|P_XO95BS|P_Y3V1Q0|P_Z7I2IJ</MAC_LABELS>
<COUNTER>26</COUNTER>
</RESPONSE>
```