• verifone

https://verifone.cloud/docs/sca-functional-specification/protocol_spec/barcode/disable_all_symbology Updated: 20-May-2025

DISABLE ALL SYMBOLOGY

This command is used to disable all symbologies.

Request Packet

Field	Rule	Туре	Minimum	Maximum	Value(s)	Description
FUNCTION_TYPE	Required	Static value	N/A	N/A	BARCODE	Type of function
COMMAND	Required	Static value	N/A	N/A	BCDISABLEALLSYMBOLOGIES	Command name
POS_RECON	Optional	Character	1	30		POS reconciliation. POS Reconciliation field to be echoed back in response to POS. Example: RetailPOS1
COUNTER	Required	Numeric	1	10		COUNTER is used for a given MAC label. Each COUNTER should be higher than the last one. This is sed to authenticate the POS. Example: 7

Field	Rule Type M	Minimum Maximum	Value(s)	Description
MAC	Base64 Required Encoded N Data	N/A N/A		Message Authentication Code. This is used to authenticate the POS.
MAC_LABEL	Required Character 1	1 50		Associated label that tells the device which MAC_KEY to use to decrypt the value of MAC. This is used to
				authenticate the POS. Example: P_JTY065

Example

Following is an example of request packet

<TRANSACTION> <FUNCTION_TYPE>BARCODE</FUNCTION_TYPE> <COMMAND>BCDISABLEALLSYMBOLOGIES</COMMAND> <MAC>...</MAC> <COUNTER>7</COUNTER> <MAC_LABEL>P_JTY065</MAC_LABEL> </TRANSACTION>

Response Packet

Field	Туре	Value	Description
RESPONSE_TEXT	Characte	r	Processor response text. Example: Command response 0
RESULT	Characte	r	This indicates the Result details. Example: SUCCESS
RESULT_CODE	Numeric	Expected result code: -1, 59001, 59006, 59040	This indicates the result code. Refer to <u>Result/Error</u> <u>Codes</u> for details.

Field	Туре	Value	Description	
TERMINATION_STATU	N Character	SUCCESS or FAILURE	This indicates the transaction termination status. This is the overall status of the transaction irrespective of approved or declined. Like, if the output is generated then the status is SUCCESS and if no output is generated then the status will be FAILURE.	
POS_RECON	Character		POS reconciliation field echoed back if sent in request. Example: RetailPOS1	
COUNTER	Numeric		Echoes counter sent in the request. Example: 7	
Transaction Performance Metric				

Note

These fields are returned, if SCAPERFMETRIC parameter (Application Parameters) is enabled.

Field	Type Value	Description
UI_TIME	Time	This indicates the time duration, for which the device screen is displayed (like error message, prompt screen, remove card screen) till any user action is performed in the command execution flow. This field is not applicable to capture the time for the Processing, Authorizing and transaction status screen. The format of the returned value would be S.sss, where S is seconds (this can be 0 to any positive integer) and sss is milliseconds. In case of any insignificant time or 0.000 value, will not be returned in the response. Example: <ui_time>44.028</ui_time>
HOST_TIME	ETime	This indicates the time taken for the Connection to the host, sending request and receives data from the host. This field also take the cumulative time for multiple requests which may sent to the host during the transaction including two legged transactions, timeout requests, Auto Last Tran requests, DCC, Credit app proxy. The format of the returned value would be S.sss, where S is seconds (this can be 0 to any positive integer) and sss is milliseconds. In case of any insignificant time or 0.000 value, will not be returned in the response. Example: <host_time>1.389<!--</td--></host_time>
CMD_TIME	Time	This field indicates the total amount of time for a command, which is executed by the application from request received to the response sent. The format of the returned value would be S.sss, where S is seconds (this can be 0 to any positive integer) and sss is milliseconds. In case of any insignificant time or 0.000 value, will not be returned in the response. Example: <cmd_time>70.765</cmd_time>

Example

Following is an example of response packet

<RESPONSE> <RESPONSE_TEXT>Command response 0</RESPONSE_TEXT> <RESULT>SUCCESS</RESULT> <RESULT_CODE>-1</RESULT_CODE> <TERMINATION_STATUS>SUCCESS</TERMINATION_STATUS> <COUNTER>7</COUNTER> </RESPONSE>